



Characteristic equation:

$$1 + \underbrace{(K_P + K_D s)}_{G_c(s)} \cdot \underbrace{\frac{1}{s^2}}_{G_p(s)} = 0$$

$$s^2 + K_D s + K_P = 0$$

To use the RL method, we need to convert it into the Evans form  $1 + KL(s) = 0$ , where  $L(s) = \frac{b(s)}{a(s)} = \frac{s^m + b_1 s^{m-1} + \dots}{s^n + a_1 s^{n-1} + \dots}$

$$1 + (K_P + K_D s) \frac{1}{s^2} = 1 + K_D \cdot \frac{s + K_P/K_D}{s^2}$$

$$\implies K = K_D, \quad L(s) = \frac{s + K_P/K_D}{s^2} \quad (\text{assume } K_P/K_D \text{ fixed, } = 1)$$