

## Rule D: Real Locus

The branches of the RL start at the open-loop poles. Which way do they go, left or right?

Recall the phase condition:

$$1 + KL(s) = 0 \quad \iff \quad \angle L(s) = 180^\circ$$

$$\begin{aligned}\angle L(s) &= \angle \frac{b(s)}{a(s)} \\ &= \angle \frac{(s - z_1)(s - z_2) \dots (s - z_m)}{(s - p_1)(s - p_2) \dots (s - p_n)} \\ &= \sum_{i=1}^m \angle(s - z_i) - \sum_{j=1}^n \angle(s - p_j)\end{aligned}$$

— this sum must be  $\pm 180^\circ$  for *any*  $s$  that lies on the RL.